Project	Catalog #	Туре	
Prepared by	Notes	Date	



Interactive Menu

- Ordering Information page 2
- Mounting Details page 3
- Product Specifications page 4
- Energy and Performance Data page 4
- Control Options page 7

Lumark

Axcent

Wall Mount Luminaire

Product Certifications & Features



































Quick Facts


- Available in 12W 116W (1,800 16,000 lumens) models
- · Full cutoff and refractive lens models available
- Energy and maintenance savings up to 95% compared to HID
- Energy efficient illumination results in up to 177LPW
- · Replaces 70W up to 450W HID equivalents

Connected Systems

- WaveLinx PRO Wireless
- WaveLinx LITE Wireless

Dimensional Details

Full Cutoff





Dimensional Data

	AXCS Small	AXCL Large
Α	8" [202mm]	11-1/2" [292mm]
В	7-1/2" [190mm]	10-3/4" [273mm]
С	3-5/8" [94mm]	4-7/8" [124mm]
D	6-1/8" [155mm]	7-1/8" [181mm]

- NOTES.

 1. DarkSky approved for 3000K CCT and warmer, with mounting options less than 10° of tilt.

 2. Refractive Lens option does not comply with DarkSky.

Ordering Information

SAMPLE NUMBER: AXCS1A-AP-347V

Domestic Preferences	Model Series ¹	LED Color Temperature	Color	Options (Add as Suffix)
[Blank]=Standard BAA=Buy American Act ²⁶ TAA=Trade Agreements Act ²⁶ BABA=Build America Buy America Act ²⁸	Full Cutoff 29 AXCS1A=12W AXCS2A=16W AXCS3A=23W AXCS4A=38W AXCS4A=45W AXCL6A=50W AXCL10A=89W AXCL112A=116W Refractive Lens AXCS1ARL=12W AXCS2ARL=16W AXCS3ARL=23W AXCS3ARL=38W AXCS4RL=50W AXCL6A=56W AXCL10ARL=59W AXCL10ARL=59W AXCL10ARL=50W AXCL10ARL=50W AXCL10ARL=50W AXCL10ARL=5116W	[Blank]=4000K, Neutral C=5000K, Cool W=3000K, Warm ²⁹	[Blank]=Carbon Bronze (Standard) WT=Summit White BK=Black AP=Grey GM=Graphite Metallic DP=Dark Platinum	347V=347V² 480V=480V² PC1=Photocontrol 120V³.4.5 PC2=Photocontrol 120-277V, 347V, 480V 4.5.6 PC2=Photocontrol 120-277V, 347V, 480V 4.5.6 PC3=Photocontrol 120-277V, 347V, 480V 4.7.8 KKIT=Knuckle Floodlight Mount TRNKIT=Trunnion Floodlight Mount SKIT=Sipfitter Floodlight Mount PMAKIT=Pole Mount Arm WPS2XX=Wavelinx Pro, SR Driver, Dimming Motion and Daylight, WAC Programmable, 7'-15' Mounting Height 4.5.16.11 WPS4XX=Wavelinx Pro, SR Driver, Dimming Motion and Daylight, WAC Programmable, 15'-40' Mounting Height 4.5.16.11 WLS2XX=Wavelinx Lite, SR Driver, Dimming Motion and Daylight, Bluetooth Programmable, 15'-40' Mounting 4.5.16.11 WLS4XX=Wavelinx Lite, SR Driver, Dimming Motion and Daylight, Bluetooth Programmable, 15'-40' Mounting 4.5.16.11 WSP/DIM-112=Integrated Sensor for Dimming Operation, 8'-12' Mounting Height 4.5.12 MSP/DIM-130=Integrated Sensor for Dimming Operation, 12'-30' Mounting Height 4.5.12 MSP-130=Integrated Sensor for ON/OFF Operation, 8'-12' Mounting Height 4.5.12 MSP-130=Integrated Sensor for ON/OFF Operation, 12'-30' Mounting Height 4.5.12 CBP-CGC-Cold Weather Battery Pack, CEC compliant 3.13.14.15.16.17 10K=10kV/10kA Surge Protection HA=50'C High Ambient 14.18 GRF-Glare Reducing Lens 19 AHD145=After Hours Dim, 5 Hours 5.20 AHD245=After Hours Dim, 6 Hours 5.20 AHD255=After Hours Dim, 7 Hours 5.20 AHD255=After Hours Dim, 7 Hours 5.20 AHD255=After Hours Dim, 8 Hours 5.20

Accessories (Order Separately) 21,27 KKIT/AXCS-XX=Knuckle and Visor Floodlight Kit (For Axcent Small)⁷
SFKIT/AXCS-XX=Slipfitter Floodlight Kit (For Axcent Small)⁷
TRNKIT/AXCS-XX=Trunnion and Visor Floodlight Kit (For Axcent Small)⁷
TRNKIT-XX-Trunnion Floodlight Kit (For Axcent Large)⁵
SFKIT-XX=Slipfitter Floodlight Kit (For Axcent Large)⁵
PMAKIT-XX=Pole Mount Kit
ISHH-01=Integrated Sensor Programming Remote ²⁵
MA1010-XX=Single Tenon Adapter for 3-1/2" 0.D. Tenon
MA1011-XX=2@180" Tenon Adapter for 3-1/2" 0.D. Tenon
MA1011-XX=Single Tenon Adapter for 2-3/8" 0.D. Tenon
MA1018-XX=2@80" Tenon Adapter for 2-3/8" 0.D. Tenon

VS/AXCS-XX=Vandal Shield Axcent Small 7,23

VS/AXCS-XX=Vandal Shield Axcent Small^{7, 22}
VS/AXCS-MS=Vandal Shield Axcent Small (With Motion Sensor) ^{7, 22}
VS/AXCS-MS=Vandal Shield Axcent Small (With Motion Sensor) ⁷
VS/AXCS-MS=Wire Guard Axcent Small (With Motion Sensor) ⁷
VS/AXCL-XX=Vandal Shield Axcent Large^{5, 22}
VS/AXCL-MS=Vandal Shield Axcent (With Motion Sensor) ^{5, 22}
WG/AXCL=Wire Guard Axcent Large⁵
WG/AXCL=Wire Guard Axcent (With Motion Sensor) ⁵
BB/AXC=Axcent Lumen Select Back Box, Carbon Bronze ²³
BB/AXC-PC=Axcent Lumen Select Back Box, Summit White ²³
BB/AXC-WT=Axcent Lumen Select Back Box with PC, Summit White ²³
BB/AXC-WT=C=Axcent Lumen Select Back Box with PC, Summit White ²³
BB/AXC-WT=C=Axcent Lumen Select Back Box with PC, Summit White ²³

- 3. Not available in 347 or 480 VAC.
- 4. Button photocontrol and any motion sensor (MSP or LWR) not offered together 5. Only available on AXCL6-AXCL12 models.
- 6. Used with 277, 347, and 480 VAC options.
- 7. Only available on AXCS1-AXCS5 models.
- 8. This configuration may contain materials that are not RoHS compliant. Contact your lighting representative for more information.
- 9 Uses deep back housing

NOTES:

Models for details

- 10. Sensor passive infrared (PIR) may be overly sensitive when operating below -20°C (-4°F). For the device to be field-configurable, requires WAC Gateway components WAC-PoE and WPOE-120 in appropriate quantities. Only compatible with WaveLinx system and software and requires system components to be installed for operation. See website for more Wavelinx application information.
- 11. Replace XX with sensor color (WH, BZ, or BK).
- 12. The ISHH-01 accessory is required to adjust parameters.

 13. Ambient operating temperature -20°C to 25°C for AXCL6 through AXCL10. Ambient operating temperature -20°C to 30°C on AXCS4 models. Ambient operating temperature -20°C to 40°C on AXCS1 through AXCS3 models

1. DesignLights Consortium® Qualified. Refer to www.designlights.org Qualified Products List under Family

2. Transformer used only when ordered with motion sensor or AXCS1 through AXCS5 or AXCL6 fixture wattages.

- 14. Not available with AXCS5 or AXCL12 models
- 15. Uses deep back housing for AXCS1, AXCLS2, AXCS3, and AXCS4 models.
- 16. Not to be mounted in upwards / inverted orientation. Downlight wall mount only for AXCS1 through AXCS4.
- 17. CBP cannot be used with PC and motion sensor (MSP). CBP can be used with PC or motion sensor (MSP). 15. Uses deep back housing for AXCS1, AXCLS2, AXCS3, and AXCS4 models.
- 16. Not to be mounted in upwards / inverted orientation. Downlight wall mount only for AXCS1 through AXCS4.

- 17. CBP cannot be used with PC and motion sensor (MSP or LWR). CBP can be used with PC or motion sensor (MSP).
- 18. Can not be ordered with CBP or PC options. 19. Use dedicated IES files on product website for lumen values and distributions.
- 20. Requires the use of PC1 or PC2 button photocontrol. See After Hours Dim supplemental guide for additional information.
- 21. Replace XX with color designation.
- 22. For use with full cutoff lens configurations only.
 23. Lumen Select functionality not available in conjunction with any motion sensor option (MSP). Photocontrol back box not available with any photocontrol or motion sensor options (PC, MSP).
- 24. Photocell only operates at 120-277V input voltages. Not for use with 347 or 480V systems.
 25. This tool enables adjustment to parameters including high and low modes, sensitivity, time delay, cutoff and more. Consult you lighting representative for more information.
- 26. Only product configurations with these designated prefixes are built to be compliant with the Buy American Act of 1933 (BAA) or Trade Agreements Act of 1979 (TAA), respectively. Please refer to <u>DOMESTIC PREFERENCES</u> website for more information. Components shipped separately may be seperately analyzed under domestic preference requirements
- 27. Accessories sold separately will be separately analyzed under domestic preference requirements. Consult factory for further information
- 28.Only product configurations with these prefixes are built to be compliant with the Buy American Act of 1933 (BAA) or the Build America Buy America Act (BABA). BABA is the minimum Government compliance requirement for the Build America Buy America standards which is part of the Infrastructure and Investment Jobs Act (IIJA). Individual Government Agencies may have more stringent compliance standards. Please refer to the DOMESTIC PREFERENCES website or consult the CLS Domestic Preferences team for more information.

Components shipped separately may be separately analyzed under domestic preference requirements. 29. DarkSky approved when ordered with 3000K or warmer CCT.

Stock Ordering Information

	Model Series ¹				
Fu	Full Cutoff Refractive Lens				
AXCS1A=12W	AXCL10A =102W	AXCS1ARL=12W	AXCL10ARL=89W		
AXCS2A=16W	AXCL12A=123W	AXCS2ARL=16W	AXCL12ARL=116W		
AXCS3A=23W	AXCL6A-347V=50W	AXCS3ARL=23W	AXCL6ARL-347V=50W		
AXCS4A=38W	AXCL8A-347V=66W	AXCS4ARL=38W	AXCL8ARL-347V=66W		
AXCS5A=45W	AXCL10A-347V=89W	AXCS5ARL=45W	AXCL10ARL-347V=89W		
AXCL6A=56W	AXCL12A-347V=116W	AXCL6ARL=50W	AXCL12ARL-347V=116W		
AXCL8A=72W		AXCL8ARL=66W			

Note: All stock configurations are 4000K color temperatures, standard Carbon Bronze finish, and wall mount configuration



AXCS / AXCL Axcent


Mounting Details


Knuckle Mount (Small) Knuckle thread: 3/4" NPS






Slipfitter Mount (Small) Tenon OD: 2-3/8" | EPA: 0.60







Slipfitter Mount (Large) Tenon OD: 2-3/8" | EPA: 0.60




Trunnion Mount (Small)







Trunnion Mount (Large)




Trunnion Mount Detail




Pole Mount Arm (Large) EPA: 1.10




Pole Mount Arm Drill Pattern



Lumen Select Back Box





Wall Mount Plate Detail (Large)





Wall Mount Plate Detail (Small)





Wavelinx Sensor



MSP Sensor

Button Photocontrol

Vandal Shield



Wire Guard





Product Specifications

Construction

- · Die-cast aluminum housing
- External back fin design extracts heat from the surface to thermally optimize design for longer luminaire life

Optics

- · Silicone-sealed optical LED chamber
- Acrylic refractive or full cutoff lens options for Type IV distributions

Electrica

- Standard universal voltage (120-277V, 50/60Hz)
- · Driver incorporates 6kV surge protection
- <20% total harmonic distortion
- 0-10V dimming driver is standard with leads external to the fixture

Mounting

- Steel wedge mounting plate fits directly to 4" standard j-box or directly to wall with the "Hook-N-Lock" mechanism
- · Stainless steel set screws
- Lumen Select Back Box accessory offers four 1/2" NPT conduit entry wire ways. Resistor Pack combinations allow field-dimming of 75% or 50% when connected to luminaire dimming leads
- Not suitable for indoor use when installed in inverted/uplight orientation

Emergency Egress

- Optional integral cold weather battery emergency egress includes emergency operation test switch, an AC-ON indicator light and a premium, maintenance-free battery pack
- The separate emergency lighting LEDs are wired to provide redundant emergency lighting. Listed to UL Standard 924, Emergency Lighting

Compliance

- cULus certified for use in -40°C to 40°C ambient environments
- Full cutoff models are IDA Certified 3000K and warmer only
- BAA domestic preference option meets BAA requirements. See DOMESTIC PREFERENCES website or consult the CLS Domestic Preferences team for more information
- FHWA and FTA agencies are utilizing their BAA rules for BABA compliance. Cooper's products with a BAA designation are manufactured in the US and utilize a BAA COTS exemption rule for compliance. To verify a configured product with specific accessories and options meet BABA Domestic Preference Requirements; submit this catalog number to Cooper Lighting Quotation team for validation by our Engineering and Manufacturing teams.
- Please refer to the <u>DOMESTIC PREFERENCES</u>
 website or consult the CLS Domestic
 Preferences team for more information.
 Components shipped separately may be
 separately analyzed under domestic preference
 requirements.
- Components shipped separately may be separately analyzed under domestic preference requirements.

Finish

 Five-stage super TGIC polyester powder coat paint, 2.5 mil nominal thickness

Shipping Data

- Small fixture=5 lbs. [2.36 kgs.]
- Small with sensor or CBP=10 lbs. [4.40 kgs.]
- Large fixture=12 lbs. [5.45 kgs.]
- Large with sensor or CBP=17 lbs. [7.73 kgs.]
- Large with sensor & CBP=21 lbs. [9.54 kgs.]

Warranty

Five year limited warranty, consult website for details. www.cooperlighting.com/legal

Energy and Performance Data

Power and Lumens (Axcent Small)

Light Engine		AXCS1A	AXCS2A	AXCS3A	AXCS4A	AXCS5A
Power (Watts)		12	16	23	38	45
Input Current @ 12	0V (A)	0.10	0.13	0.19	0.32	0.38
Input Current @ 24	0V (A)	0.05	0.07	0.10	0.16	0.19
Input Current @ 27	7V (A)	0.04	0.06	0.08	0.14	0.16
Input Current @ 34	7 V (A)	0.03	0.05	0.07	0.11	0.13
Input Current @ 48	0V (A)	0.03	0.03	0.05	0.08	0.09
Configuration						
	4000K/5000K Lumens	1,786	2,589	3,551	5,500	6,348
Full Cutoff	3000K Lumens	1,509	2,188	3,001	4,648	5,365
	BUG Rating	B1-U0-G0	B1-U0-G0	B1-U0-G0	B2-U0-G1	B2-U0-G1
	4000K/5000K Lumens	1,894	2,745	3,765	5,832	6,731
Refractive Lens	3000K Lumens	1,600	2,320	3,182	4,928	5,688
	BUG Rating	B1-U3-G2	B1-U3-G2	B1-U3-G2	B1-U4-G3	B1-U4-G3



Power and Lumens (Axcent Large)

Light Engine		AXCL6A	AXCL8A	AXCL10A	AXCL12A
Power (Watts)		50	66	89	115
Input Current @ 12	20V (A)	0.41	0.54	0.74	0.96
Input Current @ 24	10V (A)	0.21	0.27	0.37	0.48
Input Current @ 27	77V (A)	0.18	0.24	0.32	0.42
Input Current @ 34	17V (A)	0.14	0.19	0.26	0.33
Input Current @ 48	BOV (A)	0.10	0.14	0.19	0.24
Configuration					
	4000K Lumens	7,594	9,716	12,719	16,302
Full	5000K Rating	7,501	9,598	12,564	16,103
Cutoff	3000K Lumens	6,502	8,319	10,890	13,958
	BUG Rating	B2-U0-G1	B2-U0-G2	B3-U0-G2	B3-U0-G2
	4000K Lumens	7,809	10,331	13,665	16,637
Refractive	5000K Rating	7,714	10,205	13,498	16,434
Lens	3000K Lumens	6,686	8,845	11,700	14,244
	BUG Rating	B1-U4-G4	B2-U5-G5	B2-U5-G5	B2-U5-G5

Power and Lumens (Small + CBP)

Light Engin	e	AXCS1A	AXCS2A	AXCS3A	AXCS4A
Power (Watt	s)	16	20	27	42
Input Curren	it @ 120V (A)	0.13	0.17	0.23	0.35
Input Curren	nt @ 240V (A)	0.07	0.08	0.11	0.18
Input Curren	nt @ 277V (A)	0.06	0.07	0.10	0.15
Configurati	on				
Full Cutoff	4000K/5000K Lumens	742	792	789	644
Cutorr	3000K Lumens	627	670	667	545
Refractive	4000K/5000K Lumens	787	841	837	684
Lens	3000K Lumens	664	710	708	655

Note: Power and current based on full power consumption while CBP is charging. Lumen outputs are while operating in emergency mode only.

Power and Lumens Multipliers

(Lumen Select Back Box + Axcent Small)

	Configuration	~75% Nominal Output	~50% Nominal Output
Catalog Number	Material Number		Installation ctions
AXCS1A*	13109741 or 13109939 or Other	74%	50%
AXCS2A*	13109698 or 13109938 or Other	74%	50%
AXCS3A*	13109697 or 13109937 or Other	74%	50%
AXCS4A*	13109695 or 13109936	75%	40%
AXCS4A*	13495299 or 13495470 or Other	72%	50%
AXCS5A*	13109652 or 13109935	75%	40%
AXCS5A*	13495471 or 13495472 or Other	72%	50%

Power and Lumens (Large + CBP)

Light Engine		AXCL6A	AXCL8A	AXCL10A		
Power (Watts))	54	70	93		
Input Current	@ 120V (A)	0.45	0.58	0.77		
Input Current	@ 240V (A)	0.22	0.29	0.38		
Input Current @ 277V (A)		0.19	0.25	0.33		
Configuratio	n					
Full	Full 4000K/5000K Lumens		141*10W=1410			
Cutoff 3000K Lumens		122*10=1220				
Refractive 4000K/5000K Lumens		151*10=1510				
Lens	3000K Lumens		131*10=1310			

Note: Power and current based on full power consumption while CBP is charging. Lumen outputs are while operating in emergency mode only.

Power and Lumens Multipliers

(Lumen Select Back Box + Axcent Large)

Configuration		~75% Nominal Output	~50% Nominal Output
Catalog Number	Material Number		Installation ctions
AXCL6A*	13645910 or 13645979	69%	47%
AXCL8A*	13645970 or 13645984	69%	47%
AXCL10A*	13645971 or 13645989	69%	47%
AXCL12A*	13645972 & 13645993	72%	49%



Energy and Performance Data

Lumen Maintenance (Axcent Small)

Ambient Temperature	TM-21 Lumen Main- tenance (72,000 Hours)
Up to 3A	
25°C	88%
40°C	87%
50°C	87%
Up to 4A	
25°C	88%
40°C	87%
50°C	87%
Up to 5A	
25°C	87%
40°C	86%

Lumen Maintenance (Axcent Large)

Ambient Temperature	TM-21 Lumen Main- tenance (72,000 Hours)		
Up to 8A			
25°C	89%		
40°C	87%		
50°C	86%		
Up to 10A			
25°C	88%		
40°C	86%		
50°C	85%		
Up to 12A			
25°C	85%		
40°C	82%		

Lumen Multiplier

Ambient Temperature	Lumen Multiplier
10°C	1.02
15°C	1.01
25°C	1.00
40°C	0.97



Control Options

0-10V This fixture is offered standard with 0-10V dimming driver(s) for use with a lighting control panel or other control method.


Photocontrol (PC1, PC2 and PC) Optional button-type photocontrol provides a flexible solution to enable "dusk-to-dawn" lighting by sensing light levels.


After Hours Dim (AHD) This feature allows photocontrol-enabled luminaires to achieve additional energy savings by dimming during scheduled portions of the night. The dimming profile will automatically take effect after a "dusk-to-dawn" period has been calculated from the photocontrol input. Specify the desired dimming profile for a simple, factory-shipped dimming solution requiring no external control wiring. Reference the After Hours Dim supplemental guide for additional information.

Dimming Occupancy Sensor (MSP/DIM-LXX and MSP-LXX) These sensors are factory installed in the luminaire housing. When the MSP/DIM-LXX sensor option is selected, the occupancy sensor is connected to a dimming driver and the entire luminaire dims when there is no activity detected. When activity is detected, the luminaire returns to full light output. The MSP/DIM sensor is factory preset to dim down to approximately 50 percent power with a time delay of ten minutes. The MSP-LXX sensor is factory preset to turn the luminaire off after five minutes of no activity.

These occupancy sensors includes an integrated photocell that can be activated with the ISHH-01 accessory for "dusk-to-dawn" control or daylight harvesting - the factory preset is ON. The ISHH-01 is a wireless tool utilized for changing the dimming level, time delay, sensitivity and other parameters.


A variety of sensor lens are available to optimize the coverage pattern for mounting heights from 8'-30'.





WaveLinx Wireless Control and Monitoring System The WaveLinx Outdoor control platform operates on a wireless mesh network based on IEEE 802.15.4 standards enabling wireless control of outdoor lighting. Use the WaveLinx Mobile application for set-up and configuration. At least one Wireless Area Controller (WAC) is required for full functionality and remote communication (including adjustment of any factory pre-sets).

WaveLinx Wireless Sensor (WPS2 and WPS4) These outdoor sensors offer passive infrared (PIR) occupancy and a photocell for closed loop daylight sensing. These sensors are factory preset to dim down to approximately 50 percent power after 15 minutes of no activity detected. These occupancy sensors include an integral photocell for "dusk-to-dawn" control or daylight harvesting that is factory-enabled. A variety of sensor lenses are available to optimize the coverage pattern for mounting heights from 7'-40'.





Project	Catalog #	Туре	
Prepared by	Notes	Date	



Interactive Menu

- Ordering Information page 2
- Mounting Details page 3
- Product Specifications page 4
- Energy and Performance Data page 4
- Control Options page 7

Lumark

Axcent

Wall Mount Luminaire

Product Certifications & Features



































Quick Facts


- Available in 12W 116W (1,800 16,000 lumens) models
- · Full cutoff and refractive lens models available
- Energy and maintenance savings up to 95% compared to HID
- Energy efficient illumination results in up to 177LPW
- · Replaces 70W up to 450W HID equivalents

Connected Systems

- WaveLinx PRO Wireless
- WaveLinx LITE Wireless

Dimensional Details

Full Cutoff





Dimensional Data

	AXCS Small	AXCL Large
Α	8" [202mm]	11-1/2" [292mm]
В	7-1/2" [190mm]	10-3/4" [273mm]
С	3-5/8" [94mm]	4-7/8" [124mm]
D	6-1/8" [155mm]	7-1/8" [181mm]

- NOTES.

 1. DarkSky approved for 3000K CCT and warmer, with mounting options less than 10° of tilt.

 2. Refractive Lens option does not comply with DarkSky.

Ordering Information

SAMPLE NUMBER: AXCS1A-AP-347V

Domestic Preferences	Model Series ¹	LED Color Temperature	Color	Options (Add as Suffix)
[Blank]=Standard BAA=Buy American Act ²⁶ TAA=Trade Agreements Act ²⁶ BABA=Build America Buy America Act ²⁸	Full Cutoff 29 AXCS1A=12W AXCS2A=16W AXCS3A=23W AXCS4A=38W AXCS4A=45W AXCL6A=50W AXCL10A=89W AXCL112A=116W Refractive Lens AXCS1ARL=12W AXCS2ARL=16W AXCS3ARL=23W AXCS3ARL=38W AXCS4RL=50W AXCL6A=56W AXCL10ARL=59W AXCL10ARL=59W AXCL10ARL=50W AXCL10ARL=50W AXCL10ARL=50W AXCL10ARL=5116W	[Blank]=4000K, Neutral C=5000K, Cool W=3000K, Warm ²⁹	[Blank]=Carbon Bronze (Standard) WT=Summit White BK=Black AP=Grey GM=Graphite Metallic DP=Dark Platinum	347V=347V² 480V=480V² PC1=Photocontrol 120V³.4.5 PC2=Photocontrol 120-277V, 347V, 480V 4.5.6 PC2=Photocontrol 120-277V, 347V, 480V 4.5.6 PC3=Photocontrol 120-277V, 347V, 480V 4.7.8 KKIT=Knuckle Floodlight Mount TRNKIT=Trunnion Floodlight Mount SKIT=Sipfitter Floodlight Mount PMAKIT=Pole Mount Arm WPS2XX=Wavelinx Pro, SR Driver, Dimming Motion and Daylight, WAC Programmable, 7'-15' Mounting Height 4.5.16.11 WPS4XX=Wavelinx Pro, SR Driver, Dimming Motion and Daylight, WAC Programmable, 15'-40' Mounting Height 4.5.16.11 WLS2XX=Wavelinx Lite, SR Driver, Dimming Motion and Daylight, Bluetooth Programmable, 15'-40' Mounting 4.5.16.11 WLS4XX=Wavelinx Lite, SR Driver, Dimming Motion and Daylight, Bluetooth Programmable, 15'-40' Mounting 4.5.16.11 WSP/DIM-112=Integrated Sensor for Dimming Operation, 8'-12' Mounting Height 4.5.12 MSP/DIM-130=Integrated Sensor for Dimming Operation, 12'-30' Mounting Height 4.5.12 MSP-130=Integrated Sensor for ON/OFF Operation, 8'-12' Mounting Height 4.5.12 MSP-130=Integrated Sensor for ON/OFF Operation, 12'-30' Mounting Height 4.5.12 CBP-CGC-Cold Weather Battery Pack, CEC compliant 3.13.14.15.16.17 10K=10kV/10kA Surge Protection HA=50'C High Ambient 14.18 GRF-Glare Reducing Lens 19 AHD145=After Hours Dim, 5 Hours 5.20 AHD245=After Hours Dim, 6 Hours 5.20 AHD255=After Hours Dim, 7 Hours 5.20 AHD255=After Hours Dim, 7 Hours 5.20 AHD255=After Hours Dim, 8 Hours 5.20

Accessories (Order Separately) 21,27 KKIT/AXCS-XX=Knuckle and Visor Floodlight Kit (For Axcent Small)⁷
SFKIT/AXCS-XX=Slipfitter Floodlight Kit (For Axcent Small)⁷
TRNKIT/AXCS-XX=Trunnion and Visor Floodlight Kit (For Axcent Small)⁷
TRNKIT-XX-Trunnion Floodlight Kit (For Axcent Large)⁵
SFKIT-XX=Slipfitter Floodlight Kit (For Axcent Large)⁵
PMAKIT-XX=Pole Mount Kit
ISHH-01=Integrated Sensor Programming Remote ²⁵
MA1010-XX=Single Tenon Adapter for 3-1/2" 0.D. Tenon
MA1011-XX=2@180" Tenon Adapter for 3-1/2" 0.D. Tenon
MA1011-XX=Single Tenon Adapter for 2-3/8" 0.D. Tenon
MA1018-XX=2@80" Tenon Adapter for 2-3/8" 0.D. Tenon

VS/AXCS-XX=Vandal Shield Axcent Small 7,23

VS/AXCS-XX=Vandal Shield Axcent Small^{7, 22}
VS/AXCS-MS=Vandal Shield Axcent Small (With Motion Sensor) ^{7, 22}
VS/AXCS-MS=Vandal Shield Axcent Small (With Motion Sensor) ⁷
VS/AXCS-MS=Wire Guard Axcent Small (With Motion Sensor) ⁷
VS/AXCL-XX=Vandal Shield Axcent Large^{5, 22}
VS/AXCL-MS=Vandal Shield Axcent (With Motion Sensor) ^{5, 22}
WG/AXCL=Wire Guard Axcent Large⁵
WG/AXCL=Wire Guard Axcent (With Motion Sensor) ⁵
BB/AXC=Axcent Lumen Select Back Box, Carbon Bronze ²³
BB/AXC-PC=Axcent Lumen Select Back Box, Summit White ²³
BB/AXC-WT=Axcent Lumen Select Back Box with PC, Summit White ²³
BB/AXC-WT=C=Axcent Lumen Select Back Box with PC, Summit White ²³
BB/AXC-WT=C=Axcent Lumen Select Back Box with PC, Summit White ²³

- 3. Not available in 347 or 480 VAC.
- 4. Button photocontrol and any motion sensor (MSP or LWR) not offered together 5. Only available on AXCL6-AXCL12 models.
- 6. Used with 277, 347, and 480 VAC options.
- 7. Only available on AXCS1-AXCS5 models.
- 8. This configuration may contain materials that are not RoHS compliant. Contact your lighting representative for more information.
- 9 Uses deep back housing

NOTES:

Models for details

- 10. Sensor passive infrared (PIR) may be overly sensitive when operating below -20°C (-4°F). For the device to be field-configurable, requires WAC Gateway components WAC-PoE and WPOE-120 in appropriate quantities. Only compatible with WaveLinx system and software and requires system components to be installed for operation. See website for more Wavelinx application information.
- 11. Replace XX with sensor color (WH, BZ, or BK).
- 12. The ISHH-01 accessory is required to adjust parameters.

 13. Ambient operating temperature -20°C to 25°C for AXCL6 through AXCL10. Ambient operating temperature -20°C to 30°C on AXCS4 models. Ambient operating temperature -20°C to 40°C on AXCS1 through AXCS3 models

1. DesignLights Consortium® Qualified. Refer to www.designlights.org Qualified Products List under Family

2. Transformer used only when ordered with motion sensor or AXCS1 through AXCS5 or AXCL6 fixture wattages.

- 14. Not available with AXCS5 or AXCL12 models
- 15. Uses deep back housing for AXCS1, AXCLS2, AXCS3, and AXCS4 models.
- 16. Not to be mounted in upwards / inverted orientation. Downlight wall mount only for AXCS1 through AXCS4.
- 17. CBP cannot be used with PC and motion sensor (MSP). CBP can be used with PC or motion sensor (MSP). 15. Uses deep back housing for AXCS1, AXCLS2, AXCS3, and AXCS4 models.
- 16. Not to be mounted in upwards / inverted orientation. Downlight wall mount only for AXCS1 through AXCS4.

- 17. CBP cannot be used with PC and motion sensor (MSP or LWR). CBP can be used with PC or motion sensor (MSP).
- 18. Can not be ordered with CBP or PC options. 19. Use dedicated IES files on product website for lumen values and distributions.
- 20. Requires the use of PC1 or PC2 button photocontrol. See After Hours Dim supplemental guide for additional information.
- 21. Replace XX with color designation.
- 22. For use with full cutoff lens configurations only.
 23. Lumen Select functionality not available in conjunction with any motion sensor option (MSP). Photocontrol back box not available with any photocontrol or motion sensor options (PC, MSP).
- 24. Photocell only operates at 120-277V input voltages. Not for use with 347 or 480V systems.
 25. This tool enables adjustment to parameters including high and low modes, sensitivity, time delay, cutoff and more. Consult you lighting representative for more information.
- 26. Only product configurations with these designated prefixes are built to be compliant with the Buy American Act of 1933 (BAA) or Trade Agreements Act of 1979 (TAA), respectively. Please refer to <u>DOMESTIC PREFERENCES</u> website for more information. Components shipped separately may be seperately analyzed under domestic preference requirements
- 27. Accessories sold separately will be separately analyzed under domestic preference requirements. Consult factory for further information
- 28.Only product configurations with these prefixes are built to be compliant with the Buy American Act of 1933 (BAA) or the Build America Buy America Act (BABA). BABA is the minimum Government compliance requirement for the Build America Buy America standards which is part of the Infrastructure and Investment Jobs Act (IIJA). Individual Government Agencies may have more stringent compliance standards. Please refer to the DOMESTIC PREFERENCES website or consult the CLS Domestic Preferences team for more information.

Components shipped separately may be separately analyzed under domestic preference requirements. 29. DarkSky approved when ordered with 3000K or warmer CCT.

Stock Ordering Information

	Model Series ¹			
Fu	l Cutoff	Refra	ctive Lens	
AXCS1A=12W	AXCL10A =102W	AXCS1ARL=12W	AXCL10ARL=89W	
AXCS2A=16W	AXCL12A=123W	AXCS2ARL=16W	AXCL12ARL=116W	
AXCS3A=23W	AXCL6A-347V=50W	AXCS3ARL=23W	AXCL6ARL-347V=50W	
AXCS4A=38W	AXCL8A-347V=66W	AXCS4ARL=38W	AXCL8ARL-347V=66W	
AXCS5A=45W	AXCL10A-347V=89W	AXCS5ARL=45W	AXCL10ARL-347V=89W	
AXCL6A=56W	AXCL12A-347V=116W	AXCL6ARL=50W	AXCL12ARL-347V=116W	
AXCL8A=72W		AXCL8ARL=66W		

Note: All stock configurations are 4000K color temperatures, standard Carbon Bronze finish, and wall mount configuration



AXCS / AXCL Axcent


Mounting Details


Knuckle Mount (Small) Knuckle thread: 3/4" NPS






Slipfitter Mount (Small) Tenon OD: 2-3/8" | EPA: 0.60







Slipfitter Mount (Large) Tenon OD: 2-3/8" | EPA: 0.60




Trunnion Mount (Small)







Trunnion Mount (Large)




Trunnion Mount Detail




Pole Mount Arm (Large) EPA: 1.10




Pole Mount Arm Drill Pattern



Lumen Select Back Box





Wall Mount Plate Detail (Large)





Wall Mount Plate Detail (Small)





Wavelinx Sensor



MSP Sensor

Button Photocontrol

Vandal Shield



Wire Guard





Product Specifications

Construction

- · Die-cast aluminum housing
- External back fin design extracts heat from the surface to thermally optimize design for longer luminaire life

Optics

- · Silicone-sealed optical LED chamber
- Acrylic refractive or full cutoff lens options for Type IV distributions

Electrica

- Standard universal voltage (120-277V, 50/60Hz)
- · Driver incorporates 6kV surge protection
- <20% total harmonic distortion
- 0-10V dimming driver is standard with leads external to the fixture

Mounting

- Steel wedge mounting plate fits directly to 4" standard j-box or directly to wall with the "Hook-N-Lock" mechanism
- · Stainless steel set screws
- Lumen Select Back Box accessory offers four 1/2" NPT conduit entry wire ways. Resistor Pack combinations allow field-dimming of 75% or 50% when connected to luminaire dimming leads
- Not suitable for indoor use when installed in inverted/uplight orientation

Emergency Egress

- Optional integral cold weather battery emergency egress includes emergency operation test switch, an AC-ON indicator light and a premium, maintenance-free battery pack
- The separate emergency lighting LEDs are wired to provide redundant emergency lighting. Listed to UL Standard 924, Emergency Lighting

Compliance

- cULus certified for use in -40°C to 40°C ambient environments
- Full cutoff models are IDA Certified 3000K and warmer only
- BAA domestic preference option meets BAA requirements. See DOMESTIC PREFERENCES website or consult the CLS Domestic Preferences team for more information
- FHWA and FTA agencies are utilizing their BAA rules for BABA compliance. Cooper's products with a BAA designation are manufactured in the US and utilize a BAA COTS exemption rule for compliance. To verify a configured product with specific accessories and options meet BABA Domestic Preference Requirements; submit this catalog number to Cooper Lighting Quotation team for validation by our Engineering and Manufacturing teams.
- Please refer to the <u>DOMESTIC PREFERENCES</u>
 website or consult the CLS Domestic
 Preferences team for more information.
 Components shipped separately may be
 separately analyzed under domestic preference
 requirements.
- Components shipped separately may be separately analyzed under domestic preference requirements.

Finish

 Five-stage super TGIC polyester powder coat paint, 2.5 mil nominal thickness

Shipping Data

- Small fixture=5 lbs. [2.36 kgs.]
- Small with sensor or CBP=10 lbs. [4.40 kgs.]
- Large fixture=12 lbs. [5.45 kgs.]
- Large with sensor or CBP=17 lbs. [7.73 kgs.]
- Large with sensor & CBP=21 lbs. [9.54 kgs.]

Warranty

Five year limited warranty, consult website for details. www.cooperlighting.com/legal

Energy and Performance Data

Power and Lumens (Axcent Small)

Light Engine		AXCS1A	AXCS2A	AXCS3A	AXCS4A	AXCS5A
Power (Watts)		12	16	23	38	45
Input Current @ 12	0V (A)	0.10	0.13	0.19	0.32	0.38
Input Current @ 24	0V (A)	0.05	0.07	0.10	0.16	0.19
Input Current @ 27	7V (A)	0.04	0.06	0.08	0.14	0.16
Input Current @ 34	7 V (A)	0.03	0.05	0.07	0.11	0.13
Input Current @ 48	0V (A)	0.03	0.03	0.05	0.08	0.09
Configuration						
	4000K/5000K Lumens	1,786	2,589	3,551	5,500	6,348
Full Cutoff	3000K Lumens	1,509	2,188	3,001	4,648	5,365
	BUG Rating	B1-U0-G0	B1-U0-G0	B1-U0-G0	B2-U0-G1	B2-U0-G1
	4000K/5000K Lumens	1,894	2,745	3,765	5,832	6,731
Refractive Lens	3000K Lumens	1,600	2,320	3,182	4,928	5,688
	BUG Rating	B1-U3-G2	B1-U3-G2	B1-U3-G2	B1-U4-G3	B1-U4-G3



Power and Lumens (Axcent Large)

Light Engine		AXCL6A	AXCL8A	AXCL10A	AXCL12A
Power (Watts)		50	66	89	115
Input Current @ 12	20V (A)	0.41	0.54	0.74	0.96
Input Current @ 24	10V (A)	0.21	0.27	0.37	0.48
Input Current @ 27	77V (A)	0.18	0.24	0.32	0.42
Input Current @ 34	17V (A)	0.14	0.19	0.26	0.33
Input Current @ 48	BOV (A)	0.10	0.14	0.19	0.24
Configuration					
	4000K Lumens	7,594	9,716	12,719	16,302
Full	5000K Rating	7,501	9,598	12,564	16,103
Cutoff	3000K Lumens	6,502	8,319	10,890	13,958
	BUG Rating	B2-U0-G1	B2-U0-G2	B3-U0-G2	B3-U0-G2
	4000K Lumens	7,809	10,331	13,665	16,637
Refractive	5000K Rating	7,714	10,205	13,498	16,434
Lens	3000K Lumens	6,686	8,845	11,700	14,244
	BUG Rating	B1-U4-G4	B2-U5-G5	B2-U5-G5	B2-U5-G5

Power and Lumens (Small + CBP)

Light Engin	e	AXCS1A	AXCS2A	AXCS3A	AXCS4A
Power (Watt	s)	16	20	27	42
Input Curren	it @ 120V (A)	0.13	0.17	0.23	0.35
Input Curren	nt @ 240V (A)	0.07	0.08	0.11	0.18
Input Curren	nt @ 277V (A)	0.06	0.07	0.10	0.15
Configurati	on				
Full Cutoff	4000K/5000K Lumens	742	792	789	644
Cutorr	3000K Lumens	627	670	667	545
Refractive	4000K/5000K Lumens	787	841	837	684
Lens	3000K Lumens	664	710	708	655

Note: Power and current based on full power consumption while CBP is charging. Lumen outputs are while operating in emergency mode only.

Power and Lumens Multipliers

(Lumen Select Back Box + Axcent Small)

	Configuration	~75% Nominal Output	~50% Nominal Output
Catalog Material Number			Installation ctions
AXCS1A*	13109741 or 13109939 or Other	74%	50%
AXCS2A*	13109698 or 13109938 or Other	74%	50%
AXCS3A*	13109697 or 13109937 or Other	74%	50%
AXCS4A*	13109695 or 13109936	75%	40%
AXCS4A*	13495299 or 13495470 or Other	72%	50%
AXCS5A*	13109652 or 13109935	75%	40%
AXCS5A*	13495471 or 13495472 or Other	72%	50%

Power and Lumens (Large + CBP)

Light Engine		AXCL6A	AXCL8A	AXCL10A
Power (Watts))	54	70	93
Input Current	@ 120V (A)	0.45	0.58	0.77
Input Current	@ 240V (A)	0.22	0.29	0.38
Input Current @ 277V (A)		0.19	0.25	0.33
Configuratio	n			
Full	Full 4000K/5000K Lumens		141*10W=1410	
Cutoff 3000K Lumens			122*10=1220	
Refractive 4000K/5000K Lumens		151*10=1510		
Lens	3000K Lumens		131*10=1310	

Note: Power and current based on full power consumption while CBP is charging. Lumen outputs are while operating in emergency mode only.

Power and Lumens Multipliers

(Lumen Select Back Box + Axcent Large)

Configuration		~75% Nominal Output	~50% Nominal Output
Catalog Material Number			Installation ctions
AXCL6A*	13645910 or 13645979	69%	47%
AXCL8A*	13645970 or 13645984	69%	47%
AXCL10A*	13645971 or 13645989	69%	47%
AXCL12A*	13645972 & 13645993	72%	49%



Energy and Performance Data

Lumen Maintenance (Axcent Small)

Ambient Temperature	TM-21 Lumen Main- tenance (72,000 Hours)		
Up to 3A			
25°C	88%		
40°C	87%		
50°C	87%		
Up to 4A			
25°C	88%		
40°C	87%		
50°C	87%		
Up to 5A			
25°C	87%		
40°C	86%		

Lumen Maintenance (Axcent Large)

Ambient Temperature	TM-21 Lumen Main- tenance (72,000 Hours)
Up to 8A	
25°C	89%
40°C	87%
50°C	86%
Up to 10A	
25°C	88%
40°C	86%
50°C	85%
Up to 12A	
25°C	85%
40°C	82%

Lumen Multiplier

Ambient Temperature	Lumen Multiplier
10°C	1.02
15°C	1.01
25°C	1.00
40°C	0.97



Control Options

0-10V This fixture is offered standard with 0-10V dimming driver(s) for use with a lighting control panel or other control method.


Photocontrol (PC1, PC2 and PC) Optional button-type photocontrol provides a flexible solution to enable "dusk-to-dawn" lighting by sensing light levels.


After Hours Dim (AHD) This feature allows photocontrol-enabled luminaires to achieve additional energy savings by dimming during scheduled portions of the night. The dimming profile will automatically take effect after a "dusk-to-dawn" period has been calculated from the photocontrol input. Specify the desired dimming profile for a simple, factory-shipped dimming solution requiring no external control wiring. Reference the After Hours Dim supplemental guide for additional information.

Dimming Occupancy Sensor (MSP/DIM-LXX and MSP-LXX) These sensors are factory installed in the luminaire housing. When the MSP/DIM-LXX sensor option is selected, the occupancy sensor is connected to a dimming driver and the entire luminaire dims when there is no activity detected. When activity is detected, the luminaire returns to full light output. The MSP/DIM sensor is factory preset to dim down to approximately 50 percent power with a time delay of ten minutes. The MSP-LXX sensor is factory preset to turn the luminaire off after five minutes of no activity.

These occupancy sensors includes an integrated photocell that can be activated with the ISHH-01 accessory for "dusk-to-dawn" control or daylight harvesting - the factory preset is ON. The ISHH-01 is a wireless tool utilized for changing the dimming level, time delay, sensitivity and other parameters.

A variety of sensor lens are available to optimize the coverage pattern for mounting heights from 8'-30'.





WaveLinx Wireless Control and Monitoring System The WaveLinx Outdoor control platform operates on a wireless mesh network based on IEEE 802.15.4 standards enabling wireless control of outdoor lighting. Use the WaveLinx Mobile application for set-up and configuration. At least one Wireless Area Controller (WAC) is required for full functionality and remote communication (including adjustment of any factory pre-sets).

WaveLinx Wireless Sensor (WPS2 and WPS4) These outdoor sensors offer passive infrared (PIR) occupancy and a photocell for closed loop daylight sensing. These sensors are factory preset to dim down to approximately 50 percent power after 15 minutes of no activity detected. These occupancy sensors include an integral photocell for "dusk-to-dawn" control or daylight harvesting that is factory-enabled. A variety of sensor lenses are available to optimize the coverage pattern for mounting heights from 7'-40'.

