



Temporary Power Centers with GFCI Protection

50A Input
20A, 30A, 50A Output
120/240V/AC (Max.)

Temporary Power Centers

RhinoBox NEMA 3R



RB300M

Rating A	V/AC	Distribution Devices	Receptacle Rating	Protection Overload	GFCI	Catalog No.*	
50	120/240 (Max.)	(6) WR Duplex Receptacles	20A, 125V	✓	✓	□ RB300M	•
		(1) Locking Receptacle	30A, 250V	✓	–		
		(1) Locking Inlet	50A, 125/250V	–	–		
		(1) Locking Outlet	50A, 125/250V	–	–		
50	120/240 (Max.)	(6) Single Receptacles	20A, 125V	✓	✓	□ RB301M	•
		(1) Locking Receptacle	30A, 250V	✓	–		
		(1) Locking Inlet	50A, 125/250V	–	–		
		(1) Locking Outlet	50A, 125/250V	–	–		
50	120/240 (Max.)	(6) Locking Receptacles	20A, 125V	✓	✓	□ RB302M	•
		(1) Locking Receptacle	30A, 250V	✓	–		
		(1) Locking Inlet	50A, 125/250V	–	–		
		(1) Locking Outlet	50A, 125/250V	–	–		
50	120/240 (Max.)	(3) Single Receptacles	20A, 125V	✓	✓	□ RB303M	•
		(3) Locking Receptacles	20A, 125V	✓	✓		
		(1) Locking Receptacle					

RhinoBox™ Temporary Power Centers

50A Input
20A, 30A, 50A Output
120/240V/AC (Max.)

	Device Type	NEMA 1 Enclosures RB200 Series, Automatic or Manual Reset	NEMA 3R Enclosures RB300 Series, Automatic or Manual Reset
	Input	50A, 120/240V/AC, 60Hz, 3-Pole, 4-Wire Grounding	50A, 120/240V/AC, 60Hz, 3-Pole, 4-Wire Grounding
	Testing & Code Compliance	• cETLus Listed for indoor use	• cETLus Listed for indoor or outdoor use
		• Complies with NEC Articles 525 & 590	• Complies with NEC Articles 525 & 590
		• Complies with OSHA Reg. 29CFR, Part 1926, Subpart K, 1926.404, GFCI requirements	• Complies with OSHA Reg. 29CFR, Part 1926, Subpart K, 1926.404, GFCI requirements
		• Conforms to UL 1640 and CSA C22.2, no. 14	• Conforms to UL 1640 and CSA C22.2, no. 14
Specifications: Environmental	Enclosure Type	NEMA 1	NEMA 3R
Specifications: Electrical	GFCI Protection for 20A Receptacles	Yes	Yes
	Overload Protection	Yes	Yes
Materials:	Enclosure	Cold-rolled 18 gauge steel	Cold-rolled 18 gauge steel
	Legs	Cold-rolled 10 gauge steel	Cold-rolled 10 gauge steel



Temporary Power Centers with GFCI Protection

50A Input
20A, 30A, 50A Output
120/240V/AC (Max.)

Temporary Power Centers

RhinoBox NEMA 3R



RB300M

Rating A	V/AC	Distribution Devices	Receptacle Rating	Protection Overload	GFCI	Catalog No.*	
50	120/240 (Max.)	(6) WR Duplex Receptacles	20A, 125V	✓	✓	□ RB300M	•
		(1) Locking Receptacle	30A, 250V	✓	–		
		(1) Locking Inlet	50A, 125/250V	–	–		
		(1) Locking Outlet	50A, 125/250V	–	–		
50	120/240 (Max.)	(6) Single Receptacles	20A, 125V	✓	✓	□ RB301M	•
		(1) Locking Receptacle	30A, 250V	✓	–		
		(1) Locking Inlet	50A, 125/250V	–	–		
		(1) Locking Outlet	50A, 125/250V	–	–		
50	120/240 (Max.)	(6) Locking Receptacles	20A, 125V	✓	✓	□ RB302M	•
		(1) Locking Receptacle	30A, 250V	✓	–		
		(1) Locking Inlet	50A, 125/250V	–	–		
		(1) Locking Outlet	50A, 125/250V	–	–		
50	120/240 (Max.)	(3) Single Receptacles	20A, 125V	✓	✓	□ RB303M	•
		(3) Locking Receptacles	20A, 125V	✓	✓		
		(1) Locking Receptacle					

RhinoBox™ Temporary Power Centers

50A Input
20A, 30A, 50A Output
120/240V/AC (Max.)

	Device Type	NEMA 1 Enclosures RB200 Series, Automatic or Manual Reset	NEMA 3R Enclosures RB300 Series, Automatic or Manual Reset
	Input	50A, 120/240V/AC, 60Hz, 3-Pole, 4-Wire Grounding	50A, 120/240V/AC, 60Hz, 3-Pole, 4-Wire Grounding
	Testing & Code Compliance	• cETLus Listed for indoor use	• cETLus Listed for indoor or outdoor use
		• Complies with NEC Articles 525 & 590	• Complies with NEC Articles 525 & 590
		• Complies with OSHA Reg. 29CFR, Part 1926, Subpart K, 1926.404, GFCI requirements	• Complies with OSHA Reg. 29CFR, Part 1926, Subpart K, 1926.404, GFCI requirements
		• Conforms to UL 1640 and CSA C22.2, no. 14	• Conforms to UL 1640 and CSA C22.2, no. 14
Specifications: Environmental	Enclosure Type	NEMA 1	NEMA 3R
Specifications: Electrical	GFCI Protection for 20A Receptacles	Yes	Yes
	Overload Protection	Yes	Yes
Materials:	Enclosure	Cold-rolled 18 gauge steel	Cold-rolled 18 gauge steel
	Legs	Cold-rolled 10 gauge steel	Cold-rolled 10 gauge steel