



# KT-LED36HID-E26-850-D HID REPLACEMENT LED LAMP

#### **DESCRIPTION**

36W HID Replacement LED Lamp | 5000K | > 80 CRI | IP64 Rated

LAMP TYPE: HID Replacement LED
BASE TYPE: E26 (Medium)
WATTAGE: 36W
COLOR TEMPERATURE: 5000K
METAL HALIDE EQUIVALENT: 150W
COLOR RENDERING INDEX (CRI): >80
WARRANTY: 5 Years



#### **PRODUCT FEATURES**

- Replacement for conventional metal halide lamp
- 50.000 + hour lifetime
- Environmentally friendly: No mercury used
- Instant startup
- UL listed
- Suitable for use in fully enclosed fixture. Minimum lamp compartment dimensions: 8in x 8in x 9in
- Operating temperature: -40°C/-40°F to 60°C/140°F
- Integral driver, eliminates the need for external driver or ballast; includes 4kV surge protection
- IP64 rated; integrated heat sink quickly dissipates heat and guides water intrusion out of the lamp
- Do not use with standard dimmers. Not compatible with phase dimmers. Dimming functions with sensors only

#### **OPERATING SPECIFICATIONS**

#### **ELECTRICAL CHARACTERISTICS**

Input Voltage	Power Consumption	Power Factor	Input Current
120-277Vac	36W	>0.9	0.30A @ 120V 0.13A @ 277V

#### PHOTOMETRIC CHARACTERISTICS

Color Temperature (CCT)	5000K
Luminous Flux	5400 lm
Color Rendering Index (CRI)	>80
Efficacy	150 lm/W
Visible Light Area	360°

#### **SMART PORT**




On the top of the lamp is a low-voltage AUX port for lamp level sensor controls which are coming soon, Q2+ 2019.

#### RATED LIFE

L70 (Hours)	50.000

#### SPECTRAL DISTRIBUTION



#### **LUX DISTANCE CURVE**

Flux Out: 599.2 lm 1 m 190.7, 230.9 lx 200.00 cm 400.00 cm 2 m 47.68, 57.72 lx 3 m 21.19, 25.65 lx 600.00 cm 4 m 11.92, 14.43 lx 800.00 cm 7.629, 9.235 lx 1000.00 cm 5 m 6 m 5.298. 6.413 lx 1200.00 cm 7 m 3.892, 4.712 lx 1400.00 cm 2.980, 3.607 lx 8 m 1600.00 cm 9 m 2.355, 2.850 lx 1800.00 cm 10 m 1.907, 2.309 lx 2000.00 cm Angle: 90° Height Eavg, Emax Diameter






# KT-LED36HID-E26-850-D /G3 HID REPLACEMENT LED LAMP

#### WIRING INSTRUCTIONS


#### STEP 1

Disconnect power. Disconnect and remove existing ballast, capacitor, and/or ignitor (where applicable) from fixture.




#### STEP 2


Rewire for line voltage to the lamp socket. Lamp is compatible with 120-277V from single phase, three phase wye, and three phase delta systems.



#### STEP 3


Install new LED replacement lamp. Ensure lamp is operating properly when power is turned on.






\*or other line for certain three phase systems such as 120/208 three phase wye systems

#### PHYSICAL CHARACTERISTICS





#### **LAMP DIMENSIONS**

A (Illuminated Length)	5.66"
B (Body Length)	7.95"
C (Diameter)	3.34"

BASE TYPE: E26 (Medium)





### KT-LED36HID-E26-850-D /G3

### HID REPLACEMENT LED LAMP

#### **ORDERING INFORMATION**

ORDER CODE	PACK QTY.	EASY CODE	UPC
KT-LED36HID-E26-850-D /G3-DP	16	UKA-18	843654123028

#### **CATALOG NUMBER BREAKDOWN**

KT-LED36HID-E26-850-D /G3-DP

- 1 Keystone Technologies
- 2 LED Lamp
- 3 Wattage
- 4 Lamp Type
- 5 Base Type
- 6 800 Series
- 7 Color Temperature
- 8 Direct-Drive Series
- 9 Generation
- 10 Packaging Style