E26 5" Trim Series


DESCRIPTION

Full cone baffle trim with self-flange in the 5" trim family for use in recessed downlighting. Compatible for use in Halo and other housings.

Catalog #	Туре
Project	
Comments	Date
Prepared by	

SPECIFICATION FEATURES

- · Full cone metal baffle
- Torsion spring retention
- · Socket supporting
- Self-flanged trim ring sized to hide gaps caused by construction tolerances



Housings	Max Lamp Compatibility
H5ICAT H5RI	CAT 5125WB : 29W A19, 50W PAR30S,
E5ICAT E5RIC	60W PAR30L, 65W BR30 5125BB & 5125BKBB: 29W A19, 50W PAR30S, 60W PAR30L, 50W BR30
H5ICATNB	5125WB: 29W A19, 50W PAR30S,
E5ICATNB	60W PAR30L, 65W BR30 5125B & 5125BKBB: 29W A19, 50W PAR30S, 60W PAR30L, 50W BR30
H5T H5RT E5TAT E5RTA	60W A19, 75W PAR30S, 75W PAR30L, 65W BR30
H5TNB E5TATNB	60W A19, 75W PAR30S, 75W PAR30L, 65W BR30
Compatible with	Halogen, Incandescent, LED* or CFL* lamps.



5125BB Black Baffle, White Trim

5125WB White Baffle, White Trim



5125BKBB Black Baffle, Black Trim

5125

5-Inch Full Cone Baffle, Self-flange

Dimensions:

A: 4-3/4" [121mm] H: 6-5/16" [160mm] OD: 6-5/8" [168mm]

ORDERING INFORMATION

SAMPLE NUMBER: 5120WH

Trim	Finish		
5125= 5" Full Cone Baffle, Self-flange	WB=Matte white baffle, Matte white trim BB=Black baffle, White trim BKBB=Black baffle, Black trim		

HALO HOUSING COMPATIBILITY

Trim #	Style	H5ICAT	H5RICAT	E5ICAT	E5RICAT	H25ICAT	H5ICATNB	E5ICATNB	H25ICATNB
		•	•	•	•	_	•	•	_
5125	Baffle								
3123	Danie	H5T	H5RT	E5TAT	E5RTAT	H5TNB	E5TATNB		
		•	•	•	•	•	•		

For use in other's housings, refer to U.L. Classification list at www.cooperlighting.com



LISTED

Select trims are classified for use in others housings. See www.cooperlighting.com

For use in Halo listed housings.

*UL1993 listed LED & CFL equivalent lamps permitted. Consult lamp manufacturer for conditions of use. Cooper Lighting Solutions does not warranty the lamp.

