

FEATURES & SPECIFICATIONS

INTENDED USE

LED lighted exit signs for marking the means of egress in accordance with Life Safety Code NFPA 101.

CONSTRUCTION

Injection-molded, flame-retardant, high-impact, thermoplastic housing with snap-fit design components for easy installation. Universal J-box pattern and universal mounting capabilities: top, back or end mounting (canopy included). Universal chevrons are easily removed for directional indication. Fully assembled single face with extra faceplate for easy field-conversion to double face.

Letters 6" high with 3/4" stroke, with 100 ft viewing distance rating, based on UL924 standards.

OPTICS

The typical life of the LED lamp is 10 years.

ELECTRICAL

Dual-voltage input 120V or 277V AC. Emergency exits provided with test switch, status indicator and rechargeable battery.

Battery: (EL models) maintenance-free ni-cad battery provides 90 minutes of emergency power.

LISTINGS

UL Listed. Meets UL 924, NFPA 101, NFPA 70-NEC and OSHA illumination standards. Indoor damp location 50° to 104° F (10° C to 40° C) listed standard.

WARRANTY


Fixtures are covered by Lithonia Lighting 24-month warranty against mechanical defects in manufacture. Complete warranty terms located at :

www.acuitybrands.com/CustomerResources/Terms_and_conditions.aspx

All life safety equipment, including emergency lighting for path of egress must be maintained, serviced, and tested in accordance with all National Fire Protection Association (NFPA) and local codes. Failure to perform the required maintenance, service, or testing could jeopardize the safety of occupants and will void all warranties.

Note: Specifications subject to change without notice.

Actual performance may differ as a result of end-user environment and application.





Contractor Select







Height with canopy: 7-7/8"

All dimensions are inches (centimeters).

ORDERING INFORMATION

| Catalog Number | UPC | Description | Supply Voltage | Input Wattage | Pallet Qty. | Standard Carton Qty. | |
|-------------------|--------------|--------------------------------|-------------------|------------------|----------------|----------------------------|--|
| EXR LED M6 | 784231874684 | Red exit | 120/277 | 2 | 360 | 6 | |
| EXG LED M6 | 784231874806 | Green exit | 120/277 | 2 | 360 | 6 | |
| EXR LED EL M6 | 784231874738 | Red exit with backup battery | 120/277 | 2 | 360 | 6 | |
| EXG LED EL M6 | 784231874851 | Green exit with backup battery | 120/277 | 2 | 360 | 6 | |

| Accessories ¹ : Order as separate catalog number. | | | | | | | |
|--|-----------------------------|--|--|--|--|--|--|
| ELA WG1 | Wireguard (back mount only) | | | | | | |
| ELA WGEXT | Wireguard (top mount only) | | | | | | |
| ELA WGEXE | Wireguard (end mount only) | | | | | | |



LED-EXITS