

Non-Fusible Safety Switch

PS100SS



Non-Fusible Safety Switch. 100 amp, 600 vac.

features & benefits

- Top, Bottom, or back feed.
- Units are shipped without holes for conduit.
- Spot drills for locating hole saw or knockouts are provided for top, bottom, or back feed.
- End user decides at installation whether top, bottom, or back feed is appropriate.
- No closure plug kits required.
- Units are not provided with conduit hubs.



specifications

General Info

Type: Non-Fusible Safety Switch

Listing Agencies/Third Party Information

CSA Listing Info: No
CUL Listing No: No
cULus: Yes
cURus: No
Federal Spec: No
UL Listing No: No
UN SPS C: 39121403
UR: No

Dimensions

Depth U S: 10.7
Volume: 498.834
Weight: 4.3165
Width U S: 7.4
Height: 6.3

Technical Information

Amps: 100 Amp
Category Rating: Non-Fusible Safety Switches
Volts: 600VAC
Volts A C: 600

Buy American Act Compliance

Country of Origin: UNITED-STATES-OF-AMERICA
Buy American Act Status: Buy American Act Compliant