

## ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr. 75964-0000, TX Nacogdoches Phone: 936-569-7941 Fax: 936-560-4685



## S10N06A07N 7.5KVA Buck Boost Transformer 1PH 120X240-16/32V Eaton Corp

Catalog Number	S10N06A07N	
Manufacturer	Eaton Corp	
Description	Eaton General Purpose Encapsulated Transformer, Buck-Boost General-Purpose Encapsulated Transformer, Ep, Aluminum, Nema 3R, 178, 60 HZ, Single-Phase, 120 V, 240 V, 16/32 V, None, 115 °C Rise, 7.5 Kva, Indoor-Outdoor, 509B	
Weight per unit	123.0 (lbs/each)	
Product Category	20081031151214	
eatures		
connection	509B	
design	EP	
dimensions	9.8900 IN X 10.3800 IN X 16.0000 IN	
frame	178	
Number of Phases	Single-phase	
Primary Voltage	120 V, 240 V	
Secondary Voltage	16/32 V	
escriptions		
Description	7.5KVA BUCK BOOST TRANSFORMER 1PH 120X240-16/32V	
extra long description	ETN S10N06A07N 7.5KVA Buck Boost TX	
Features	Eaton's EP (single-phase) and EPT (three-phase) general purpose encapsulated dry-type transformers are of the two-winding type, encapsulated (potted) in a mix of epoxy coated sand and gravel, and are available in a wide variety of primary and secondary voltage combinations. General purpose encapsulated transformers are designed, manufactured and tested in accordance with all of the latest applicable ANSI, NEMA and IEEE standards, and are designed for continuous operation at rated kVA.	
Long Description	Eaton General purpose encapsulated transformer, buck-boost general-purpose encapsulated transformer, EP, aluminum, NEMA 3R, 178, 60 Hz, single-phase, 120 V, 240 V, 16/32 V, NONE, 115 °C rise, 7.5 KVA, indoor-outdoor, 509B	
Product Type	7.5KVA Buck Boost TX 1PH 120X240-16/32V	
lanufacturer Information		
Brand	EATON CUTLER-HAMMER	
GTIN	00786680103490	
Manufacturers Part Number	S10N06A07N	
UPC	786680103490	



## ELLIOTT ELECTRIC SUPPLY

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr. 75964-0000, TX Nacogdoches Phone: 936-569-7941 Fax: 936-560-4685

<b>Taxonomies</b>	, Classifications, a	nd Categories
-------------------	----------------------	---------------

Category Description	BUCK & BOOST TRANSFORMERS
Туре	Encapsulated transformer
Packaging	
Carton	1
Weight Per each	123
Uses, Certifications, and Standard	

## Use

Application Co	ommercial / Institutional Buildings / Structures - Commercial /
<u>In</u>	stitutional Buildings / Structures - Other
Frequency Rating 60	0 Hz
standard U	L Listed
Temperature Rating 1	15 °C rise