

## **FEATURES & SPECIFICATIONS**

INTENDED USE — SBL LED wraparound provides a digital lighting platform to deliver general ambient lighting for surface-mount applications. The SBL provides a similar look to that of an existing fluorescent wrap with all of the excellent benefits of LED: energy savings, long life, and maintenance savings. Ideal for closets, storage rooms, and offices.

**CONSTRUCTION** — Linear side prisms control brightness, pyramidal bottom prisms minimize lamp image. Continuous side flanges on fixture body provide light trap and continuous diffuser support to prevent accidental opening and simplify maintenance. Full depth, white enamel end plates.

Die-formed from code gauge cold-rolled steel. Channel cover snaps into place without the use of tools. Full end cap factory installed to reduce job site labor.

**OPTICS** — The translucent white diffuser reduces glare and pixilation without impacting performance. **ELECTRICAL** — Long-life LEDs, coupled with high-efficiency drivers, provide superior quantity and quality

of illumination for extended service life. 90% LED lumen maintenance at 50,000 hours (L90/50,000). The LEDs have a CRI of 82.

eldoLED driver options deliver choice of dimming range and choices for control, while assuring flicker-free, low-current inrush, 89% efficiency and low EMI.

Pair the SBL with the fixture mount Sensor Switch LSXR sensor for additional energy savings when the space is unoccupied. The LSXRHL sensor dims the fixture down to a low-level setting when there is no occupancy. This option is ideal for stairwells, back rooms, and closets due to the low occupancy level in those spaces.

Optional nLight® embedded controls continuously monitor system performance, allow for constant lumen management / compensation function, facilitate simple "plug-and-play" network and controls upgrading via Cat-5 cable. Ballast disconnect provided where required to comply with US and Canadian codes.

LISTINGS — CSA certified to meet U.S. and Canadian standards.

Damp listed.

DesignLights Consortium® (DLC) qualified product. Not all versions of this product may be DLC qualified. Please check the DLC Qualified Products List at www.designlights.org/QPL to confirm which versions

**BUY AMERICAN ACT** — Product with the BAA option is assembled in the USA and meets the Buy America(n) government procurement requirements under FAR, DFARS and DOT regulations. Please refer to www. acuitybrands.com/buy-american for additional information.

**WARRANTY** — 5-year limited warranty. This is the only warranty provided and no other statements in this specification sheet create any warranty of any kind. All other express and implied warranties are disclaimed. Complete warranty terms located at: www.acuitybrands.com/support/warranty/terms-andconditions

**Note:** Actual performance may differ as a result of end-user environment and application. All values are design or typical values, measured under laboratory conditions at 25 °C. Specifications subject to change without notice.

umber	
otes	
pe	

Square-basket LED Wraparound













# \*\* Capable Luminaire


This item is an A+ capable luminaire, which has been designed and tested to provide consistent color appearance and out-of-the-box control compatibility with simple commissioning.

- All configurations of this luminaire meet the Acuity Brands' specification for chromatic consistency
- This luminaire is part of an A+ Certified solution for nLight® control networks when ordered with drivers marked by a shaded background\*
- This luminaire is part of an A+ Certified solution for nLight control networks, providing advanced control functionality at the luminaire level, when selection includes driver and control options marked by a shaded background\*

To learn more about A+, visit www.acuitybrands.com/aplus.

\*See ordering tree for details

**DECORATIVE RESIDENTIAL** SBI 4



ORDERING INFORMATION

Lead times will vary depending on options selected. Consult with your sales representative.

Example: SBL4 4000LM 80CRI 35K MIN10 GZT MVOLT

SBL4							
Series	Lumens <sup>1</sup>	CRI Color temperature N		Minimum Dimming Level	Dimming	Voltage	
SBL4 4' LED w	3000LM 3000 lumens 4000LM 4000 lumens 4800LM 4800 lumens 6000LM 6000 lumens 7200LM 7200 lumens	80CRI 80 CRI	30K 3000 K 35K 3500 K 40K 4000 K 50K 5000 K	MIN10 Dims to 10%² MIN1 Dims to 1%³ NODIM On/off, non-dimming⁴ SLD Step-level dimming⁴	(blank) none <sup>10</sup> GZT Generic 0-10V Dimming  ZT eldoLED 0-10V Dimming	MVOLT 120-277V 347 347V <sup>5,11</sup>	

Emergenc	y Options	Control Input	/ Lumen Management Options <sup>10</sup>	Occupan	cy Control Options	0ccu	pancy Sensor Technology Option	Option	ns
EL7L  EL14L  E10WLCP	700 nominal lumen battery pack (Noncompliant with CA T20) <sup>6</sup> 1400 nominal lumen battery pack (Noncompliant with CA T20) <sup>6</sup> EM Self-Diagnostic battery pack, 10W Constant Power, Certified in CA Title 20 MAEDBS <sup>6</sup> for use with nLight on generator supply EM power <sup>7</sup>	NLIGHT CL80 NLIGHT	nLight enabled nLight enabled, constant lumen output, 80%	LSXRHL	Sensor Switch® fixture mount sensor with High/Low occupancy operation®.9 Sensor Switch® fixture mount sensor with on/off occupancy operation®	PIR	Passive Infrared <sup>12</sup>	BAA BDP	Buy America(n) Act Compliant Factory Installed Ballast Disconnect Plug

### ORDERING INFORMATION

Catalog number	UPC	Description	Lumens	Color temperature	Voltage	Wattage	Pallet qty	Standard carton qty.
SBL4 347 LP835	190887855692	4' LED Wraparound	3,933	3500 K	347	36	70	1
SBL4 347 LP840	190887856675	4' LED Wraparound	3,994	4000 K	347	36	70	1

#### Notes

- Approximate lumen output.
- Requires GZT control option.
- Requires GZT, ZT, or NLIGHT control.
- Not available with Control or Sensor Options. Not available with SLD option.
- Not available with 7200LM option.
- nLight EMG option requires a conection to existing nLight network. Power is provided from a separate N80 or N100 enabled fixture. Requires NLIGHT.
- 8 Requires MIN1, ZT and PIR options.
- Dims to approximately 10% light output when unoccupied.
- unioccupied.

  When Control Input/ Lumen Management option specified leave Dimming section blank.

  1347 not available with battery option

  Only available with Occupancy Control option.

Performance Data								
Lumen Package	Lumens	Input Watts	LPW					
3000LM 80CRI 30K	3165	25.5	124					
3000LM 80CRI 35K	3236	25.5	127					
3000LM 80CRI 40K	3286	25.5	129					
3000LM 80CRI 50K	3407	25.5	133					
4000LM 80CRI 30K	3847	32.4	119					
4000LM 80CRI 35K	3933	32.4	121					
4000LM 80CRI 40K	3994	32.4	123					
4000LM 80CRI 50K	4141	32.4	128					
4800LM 80CRI 30K	4698	40.5	116					
4800LM 80CRI 35K	4802	40.5	119					
4800LM 80CRI 40K	4877	40.5	120					
4800LM 80CRI 50K	5057	40.5	125					
6000LM 80CRI 30K	5985	49.9	120					
6000LM 80CRI 35K	6119	49.9	123					
6000LM 80CRI 40K	6214	49.9	125					
6000LM 80CRI 50K	6443	49.9	129					
7200LM 80CRI 30K	7052	61.9	114					
7200LM 80CRI 35K	7209	61.9	117					
7200LM 80CRI 40K	7321	61.9	118					
7200LM 80CRI 50K	7591	61.9	123					



Sensor	Curital	I CVDUI	Cameau

Lens type: 10 - Low Mount 360° coverage

Dimming: HL - High/Low Occupancy operation

**Min Dim Level: 3V** - approximately 10% light output when unoccupied

Time Delay: 5M - 5 minutes

#### How to Estimate Delivered Lumens in Emergency Mode


Use the formula below to estimate the delivered lumens in emergency mode.

#### Delivered Lumens = 1.25 x P x LPW

P= Ouput power of emergency driver. P= 10W for E10WLCP option.  $LPW=Lumen\ per\ watt\ rating\ of\ the\ luminaire.\ LPW\ information\ available\ in\ Performance\ Data\ section.$ 

## **PHOTOMETRICS**

#### SBL4 4000LM 80CRI 35K



)°	CF	Sumn	nary				
)°		0°	90				
	0°	1279	1279				
)°	5°	1275	1281				
	15°	1224	1240				
	25°	1118	1139				
	35°	962	997				
	45°	780	829				
	55°	596	657				
	65°	414	497				
)°	75°	242	344				
	85°	91	203				
	90	15	132				

#### Coefficients of Utilization

pt				2	20%									
рс	80%		70%		50%		Zonal Lumen Summary							
pw	70%	50%	30%	50%	30%	10%	50%	30%	10%	Zone	Lumens	% Lamp	% Fixture	
0	117	117	117	114	114	114	107	107	107	0° - 30°	979	24.9	24.9	
1	106	101	96	98	94	90	92	89	86	0° - 40°	1583	40.2	40.2	
2	96	88	80	85	78	73	80	75	70	0° - 60°	2748	69.9	69.9	
3	88	77	68	75	67	61	71	64	59	0° - 90°	3660	93.1	93.1	
r 4	80	68	59	66	58	51	63	56	50	90° - 120°	° 182	4.6	4.6	
4 25 5	74	61	51	59	51	44	56	49	43	90° - 130°	° 221	5.6	5.6	
՝՝ 6	68	55	46	53	45	39	51	43	38	90° - 150°	263	6.7	6.7	
7	63	49	41	48	40	34	46	39	33	90° - 180°	273	6.9	6.9	
8	59	45	37	44	36	30	42	35	30	0° - 180°	3933	100.0	100.0	
9	55	41	33	41	33	27	39	32	27					
10	51	38	30	37	30	25	36	29	24					

## **MOUNTING DATA**

Suspension Kit Ceiling Types: F1 for use with most T-bar and screw slot grid ceiling applications. Designed for on-grid and off-grid installations.

F2 for use with recessed or surface-mount horizontal J-box applications.


For unit or row installation; surface or suspend mounting.

 $Individual\ installation --- Two\ single-stem\ hangers\ required.$ 

 $For aircraft \ cable, one \ STACG\_, \ STACGF\_, \ or \ STACGE\_required \ for \ each \ suspension \ point.$ 

Note: 2' configurations with emergency option cannot be stem mounted.

See ACCESSORIES below for hanging devices.





## **DIMENSIONS**

All dimensions are inches (centimeters) unless otherwise noted.

